

I'm not a bot





1. First, make sure that Genie receiver is connected to TV and power source, and that it's turned on. 2. Ensure you're using a Genie remote with model number RC-73 or RC-72. 3. Turn on your TV and switch to Genie receiver input channel if needed. 4. Aim the remote at its receiver for clear connection. 5. Press MUTE and ENTER buttons to start setup process. 6. Release when prompted by green light flashes twice. 7. Wait for confirmation message "Your remote is now setup for RF" appears on-screen. 8. If programming audio source, ensure it's connected and turned on. 9. Press MENU button to open settings menu. 10. Select Settings & Help, then REMOTE CONTROL option. To set up your Genie remote, start by ensuring that your Genie receiver is plugged in and powered on. Make sure you're using a compatible Genie remote, which can be identified by its model number. Turn on your TV and switch to the correct input channel if necessary. Point your remote at the receiver and press and hold the MUTE and SELECT buttons until the light blinks twice. Release the buttons and enter the pairing code by typing 961 and pressing channel up and ENTER. When prompted, press OK and wait for the "Your remote is now set up for RF" message to appear on your TV. Next, turn on the component you want to program, such as a TV or audio device. Press the MENU button to open the on-screen menu, then select Settings & Help and navigate to Settings. In the Remote Control section, select Program Remote and follow the on-screen instructions to set up your remote for your selected component. Setting Up Your Genie Remote: A Step-by-Step Guide To program your Genie remote, follow these steps: 1. Choose a component to set up and select either "Program a TV" or "Program an Audio Device." 2. Follow the on-screen instructions provided by your Genie receiver. 3. For TVs, you'll need to select a manufacturer and television model before setting up your remote. 4. Find your TV's DIRECTV programming code by visiting in your browser. Click your Genie remote's model number, then select "TV" and enter your TV's model number. 5. Ensure your Genie receiver is plugged into your TV and a power source, and that it's powered on. 6. Verify you're using the correct Genie remote (RC-73, RC-72, RC-71B, or RC-71). 7. Turn on your TV and switch to the Genie receiver's input channel if necessary. 8. Point your Genie remote at its receiver and have a direct line of sight. 9. Press and hold the MUTE and ENTER buttons until you see the lights blink twice, then release. 10. Repeat step 9 with the MUTE and SELECT buttons until the lights flash twice, then release. 11. Enter your TV's code by typing it in and pressing ENTER. 12. The rest of the setup should occur automatically. Note: Common codes for DIRECTV Ready TVs include Samsung (54000), Sony (54001), and Toshiba (54002). Is an RC73 remote only compatible with IR signals and unable to be programmed for RF signals, which are used by the DirecTV Genie receiver? The RC73 is actually designed as an RF remote control for use with the DirecTV Genie receiver. However, it can send IR commands to TVs and other devices. According to customer support from DirecTV, the RC73 cannot be programmed to turn audio devices on and off. Only the volume can be controlled. If you're having trouble with your Direct TV remote, try checking if the receiver is turned on and adjusting your input settings.

[How to program directv remote to tv.](#) [How do i manually program my directv remote to my tv.](#) [How to use directv remote to control tv.](#) [How to program a directv remote.](#) [How to set up directv remote control with tv.](#)